



Utility model  
29822508.5

## Schuko-Test FI/RCD

### Socket tester with RCD/FI tripping

#### Functions

- Fast and effective testing of 30 mA RCD/FI
- Testing for correct/incorrect wiring
- Connection test for individual conductors (L-N-PE)
- PE fault detection

#### Product information

- True PE fault detection via LCD and contact electrode
- Detection of wiring faults with classic protective earthing

#### Product highlights

- Clear and reliable indication of PE faults via LCD screen

### Technical specifications

Nominal voltage	230 V AC $\pm 10\%$
Frequency range	50...60 Hz
RCD/FI test current	30 mA
RCD/FI test time	< 300 ms
Contact voltage with break-off at monitoring	20...25 V AC/DC
PE fault detection	
Response threshold	25 V AC
Safety cert.:	DIN VDE 0411/EN 61010/IEC 61010
Measurement category	CAT II/300 V
Pollution degree	2
Power supply	from mains voltage
Dimensions	70 x 55 x 86 mm
Weight	approx. 75 g

### Included:

- 1 x Schuko test FI/RCD
- 1 x user manual

### Ordering Information:

Description	Model	Article no.
Schuko test FI/RCD	9080*	3530534

\* Packing unit of 10 items (also available individually)

\* Tester is available for countries with a Schuko plug only

## Socket test

FI/RCD testers contain a display for testing the pin assignment specifically intended for testing an earthed socket.

With all RCD/FI testers, the contact voltage is monitored and any PE faults are clearly displayed.

